

Constant voltage LED Control

Power supply and control Led 24V



LB-50/One

Control unit for 24Vdc LEDs, 4 outputs with settable mode for white or single-color LEDs, CCT, RGB and RGBW. 433.92MHz radio receiver. 1 wired input settable as button or switch. Integrated WiFi module for remote control via OneSmart App and voice control. Integrated power supply, max 50W.



LB-100/One

Control unit for 24Vdc LEDs, 4 outputs with settable mode for white or single-color LEDs, CCT, RGB and RGBW. 433.92MHz radio receiver. 1 wired input settable as button or switch. Integrated WiFi module for remote control via OneSmart App and voice control. Integrated power supply, max 100W.



LB-150/One

Control unit for 24Vdc LEDs, 4 outputs with settable mode for white or single-color LEDs, CCT, RGB and RGBW. 433.92MHz radio receiver. 1 wired input settable as button or switch. Integrated WiFi module for remote control via OneSmart App and voice control. Integrated power supply, max 150W.

Code	LB-50 / -100 / -150 /One
Power supply	230 Vac
Integrated power supply	50 W / 100W / 150W
Load	Led 24 Vdc Max 50W
Settable function	Dimmer 1 output, CCT, RGB/W
Inputs	1 NO push button
No. Prog. transmitters	30
Radio Frequency	433.920 MHz ISM
WiFi Frequency	WiFi 2,4GHz
Smart remote control	App OneSmart
Voice Control	Google home, Alexa Amazon
IP protection	IP55
Operating Temperature	-20 +55 °C
Dimensions	310x70x80 mm

To order the radio versions without Smart WiFi, remove "/ONE" from the code

CONNECTIONS

