

Touch-1SP

Wireless motion sensor

Automatic control

Wireless motion sensor with settable detection distance and light threshold. Radio control or sensor functions can be activated using the touch keys: sensor activation/deactivation On/Off (press and release) and dimmer (press and hold).

Small size 40x40x10mm, ideal for installation on desks and walk-in closets.



TOUCH-1SP



Touch button with radio functions On-Off-Dimmer

Touch button for activation / deactivation sensor

Code	Touch-1SP
Power supply	Battery CR2450
Battery life	About 3 years
Encoding	Rolling code
Radio frequency	433,92 MHz
Signal range	80 m in open spaces 20 m in buildings
Detection distance	Set from 30 cm to 6 m
Detection angle	cone of 120°
Timing	Set from 1 min to 4 hr.
Brightness threshold	6 different levels
Dimensions	40 mm x 40 mm x 10 mm